

Exercise Icebreaker

Use correct radio procedures to pass information:

Example

MRA79B = This is MRA79C = Over

MRA79C = This is MRA79B = Over

**MRA79B = This is MRA79C =
Name of place at GRID TQ292992 =
Over**

MRA79C = This is MRA79B =
Wait out

MRA79C = This is MRA79B =
Name of place at GRID TQ292992 is
Botany Bay = Over

**MRA79B = This is MRA79C =
Correct = Out**

If an incorrect reply is given:

**MRA79B = This is MRA79C =
WRONG = Verify your answer =
OVER**

Tips

Write the grid references down before you send them, or as you receive them.

You can use town names, rivers, road names/numbers, and other signs.

Practice using other prowords like 'SAY AGAIN', 'I SPELL', 'FIGURES', 'CORRECT', 'CORRECTION' 'NOTHING HEARD' and 'SPEAK SLOWER'.

Phonetics

A	ALPHA
B	BRAVO
C	CHARLIE
D	DELTA
E	ECHO
F	FOXTROT
G	GOLF
H	HOTEL
I	INDIA
J	JULIET
K	KILO
L	LIMA
M	MIKE
N	NOVEMBER
O	OSCAR
P	PAPA
Q	QUEBEC
R	ROMEO
S	SIERRA
T	TANGO
U	UNIFORM
V	VICTOR
W	WHISKY
X	X-RAY
Y	YANKEE
Z	ZULU

1	WUN
2	TOO
3	TREE
4	POWER
5	FIFE
6	SIX
7	SEVEN
8	AIT
9	NINER
0	ZERO

Prowords

AFFIRM	Yes
CORRECT	Your transmission is correct.
CORRECTION	I made a mistake in this transmission. The correct version is...
FIGURES	I'm about to send a group of numbers - write them down...
FROM	The following message is from...
GRID	I'm about to send a grid reference
I SPELL	I'll spell the next word(s) phonetically
NEGATIVE	No
NOTHING HEARD	I didn't hear a reply.
OUT	End of transmission. Reply NOT required.
OVER	End of transmission. Reply required.
RELAY TO	Send the following message to...
ROGER	Message received and understood.
SAY AGAIN	Please retransmit entire transmission. Can be used with 'ALL AFTER' or 'WORD AFTER', etc.
SPEAK SLOWER	You need to slow down. Might be used with 'SAY AGAIN'.
THIS IS	My callsign follows...
UNKNOWN STATION	Used when calling a station whose callsign you don't know.
WAIT OUT	Message received. Reply will follow soon.
WILCO	Message received. I <u>will</u> <u>comply</u> .
WRONG	Your transmission is wrong. (The correct version is...)

Appointment Titles

SUNRAY	OC (Person in charge of Sqn, Unit or exercise)
SUNRAY MINOR	OCs 2IC
PRONTO	Signals (Person in charge of radio comms for Sqn or exercise)
PRONTO MINOR	Signals 2IC

Radio Checks

LOUD	CLEAR
GOOD	READABLE
WEAK	DISTORTED
VERY WEAK	INTERMITTENT
FADING	WITH INTERFERENCE
	UNREADABLE

Authentication

ALPHA	Sqn No
BRAVO	Sqn No in reverse
CHARLIE	Sqn No + date
DELTA	Callsign No + date